

## 3600 to 3800MHz –Band Stop Filter

### Design Features


- ◆ High RF performance, ultra-competitive price.
- ◆ Military, space and commercial applications.
- ◆ Custom design available upon request.
- ◆ Support one year standard warranty.

### RF Characteristics

Model Number	Band Reject Frequency (MHz)	Pass Band Frequency	Band Reject Rejection Min(dB)	VSWR Max	Insertion Loss Max(dB)	Power (W)	Connector Type	Temp.(°C)
UIYBSF17235A3600T3800SF	3600 ~ 3800	DC~3350MHz 4050~7000MHz	50	2.0	1.5	50	SMA-F	-55 ~ +85

<sup>2</sup> Listed are specific frequency ranges and other tailor-made ranges are available.  
<sup>2</sup> Please provide the below information when inquiring and mark \* is required.  
 \* 1. The specific pass band frequency range.  
 \* 2. The specific rejection and frequency.  
 3. Other special requests (such as Insertion Loss, VSWR, Connector Type, Dimension, etc.).

### Mechanical Drawing



Unit: mm/ inch, General part tolerance is  $\pm 2\%$  unless otherwise stated.

Ver. 5